

WARNING

Risk of electric shock. Disconnect main power at circuit breaker before installing or servicing the fixture








1. Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
2. To prevent wiring damage or abrasion. Do not expose wiring to edges of sheet metal or other sharp objects.
3. Suitable for wet locations
4. Suitable for type IC or suitable for type NON-IC.
5. Use only in open luminaires.
6. This device is not intended for use with emergency exits.

GENERAL: All electrical connections must be in accordance with local and national electrical code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

ASSEMBLY AND INSTALLATION

This IC/AT fixture is intended for use in suspended ceilings(with or without insulation).

- Shut off power before installation
- Prepare fixture for recessed installation. For 3.5" and 4" J-Boxes install the provided mounting bracket using the two included M4x20 screws. For 2.75" J-Boxes the mounting bracket is not needed. (FIG1,2 & 3)
- Remove lens by twisting counterclockwise.(FIG4)
- Connect supply wires to the wires on the fixture using wire nuts or quick connectors. Connect white to white, black to black, and the copper wire to copper wire as a ground connection.(FIG5)
- Arrange the wires back into the junction box.
- If the fixture is being installed to a 3.5" or 4" J-Box, align the fixture up to the appropriate holes on the mounting bracket. Use 2 of the included M4x20 screws to attached fixture to J-Box. If the fixture is being installed to a 2.75" J-Box, align the fixture up to the appropriate holes built into the fixture. Use 2 of the included M4x40 screws to attached fixture to J-Box The fixture should be flush with ceiling.(FIG6)
- Install the lens back onto the fixture by turning the lens clockwise until it locks in place.(FIG7)



MOUNTING BRACKET
(For use with 3.5" & 4" J-Boxes)



J-Box Screws



Wire Nuts