

# **LED EMERGENCY** DRIVER

EMG - 2DC PAGE 1 OF 3

Project:

Notes:

Catalog #:

#### **Key Features & Benefits:**

- High Temperature, Nickel Cadmium Battery for Long Life
- 13-60VDC for Wide Range of LED Loads
- RoHS Compliant
- UL 924 and Tested to CSA C.22.2 No. 141-15 Emergency Lighting Compliant
- Meets CEC Title 20 (California Energy Commission) Efficiency Standards
- Test Switch Indicator: 2W ITS (2-Wire Illumination Test Switch)



Date:









#### **Technical Specifications:**

ESL-EMG-	2DC-xxW*	5 Watts <sup>†</sup>	9 Watts	15 Watts <sup>†</sup>	25 Watts <sup>†</sup>	
Input	Rated Current	0.05A (Max)	0.06A (Max)	0.07A (Max)	0.1A (Max)	
	Rated Power	3.5 Watts (Max)	4 Watts (Max)	5.5 Watts (Max)	7 Watts (Max)	
	Rated Voltage	100 - 277 VAC, 50 - 60Hz				
Output	Emergency Output Power	5 Watts	9 Watts	15 Watts	25 Watts	
	Output Voltage	13~60VDC	14~60VDC	15~60VDC	25~60VDC	
	Output Current	1A (Max)				
	Output Current of AC Driver	5A (Max)				
	Operation Frequency	320kHz≥f≥50kHz				
Emergency	Emergency Operation	≥90 Minutes				
	Charging Time	24 Hours				
	Charging Current	A80.0	0.11A	0.19A	0.23A	
	Power Factor	≥0.50				
Environment	Operating Temperature	32°F - 122°F				
		0°C - 50°C				
	Case Tc	Max. 158°F (70°C)				
	Weight	0.37 lbs (without battery)				

<sup>\*</sup> XX = Output Power (5, 9, 15 or 25 Watts)

<sup>&</sup>lt;sup>†</sup> These products are not stocked. Contact factory for lead times.




# **LED EMERGENCY** DRIVER

### **Technical Specifications**

PAGE 2 OF 3


#### **Dimensions:**

#### EMG-2DC:






#### Test Switch:



#### **Battery Pack:**




BATTERY PACK	L	w	D
9.6V, 1500mAh	3.94" ±0.08"	2.24" ±0.08"	Ø 0.55" ±0.04"
10.8V, 2100mAh	5.91" ±0.06"	2.01" ±0.06"	Ø 0.67" ±0.04"
10.8V, 3800mAh	8.39" ±0.12"	2.22" ±0.04"	Ø 0.74" ±0.02"
14.4V, 4500mAh	7.72" ±0.12"	3.01" ±0.06"	Ø 1.02"



## **LED EMERGENCY** DRIVER

Wiring PAGE 3 OF 3

#### **Typical Wiring Diagram:**





www.eslvision.com