<u>DQC1</u> DRIVER

13 Watts - Single Output Driver

Key Features & Benefits:

N

- Universal AC Input / Full Range (up to 305 VAC)
- Built-in Active PFC Function
- Protections: Short Circuit / Over Voltage / Over Temperature
- Suitable for Dry / Damp Locations
- Easy Installation with ESL Vision Quick Connect Series
- 7 Year Warranty



Technical Specifications:

Input

Input Voltage: 100 - 277 VAC Power Factor: 0.98 / 120 VAC, 0.90 / 277 VAC Total Harmonic Distortion: 20% Frequency Range: 47~63Hz Efficiency: 88% AC Current: .108 A / 120 VAC, .046 A / 277 VAC

E4747

Output

DC Voltage: 36 VDC

Rated Power: 13W

Line Regulation: 3%

Load Regulation: 2%

Rated Current: 320 mA

Voltage Range: 28-42 VDC

us

Project:

Notes:

Catalog #:

Environment

E


A DECEMBER OF THE COLOR

Working Temperature: -20 ~ 50°C Max Case Temperature: 65°C Working Humidity: 20 -70% RH

θ

Date:

AC Current: 108 A / 120 VAC, .046 A / 277 V.



Example Part Number: ESL-DQC1-13W-1L



Copyright © 2017 ESL Vision, LLC. All rights reserved. Rev: 09.13.17